

# MIDIBox AY 3 8912 - PATCH MENU

Access the **PATCH MENU** via **F1**

## The Patch Menu:

LCD ROW	Func.	Data	Memo
1	NAME:	PATCHNAME	Edit the Patchname here
2	NR :	0 to 127	Select the Patch here (Patch 0 = PIC internal Patch / 1 to 127 = Bankstick Patches)
3	DO :	L W F	Do <b>L</b> oad Patch, <b>W</b> rite Patch, <b>F</b> ormat Bankstick1
4	status	(info)	( <b>W</b> : OK, <b>L</b> : OK, <b>F</b> : BS PATCH 1-127)

## Annotation - Editing:

LCD ROW	EDIT	KEYS
1	NAME	Use A-Z, 0-9, SPACE = " _ ", after Patchname Editing the user can delete the Patchname via INST DEL key
2	Nr.	Use crsr ← → (+ / -)
3	Do	Use L W F
4	status	(info)

## Annotation:

- Bankstick = Bankstick1 by default
- A " ! " before the [Patchname] (@LCD ROW1) indicates, that the Patch is NOT loaded yet.
- The Fx Data will be stored (via current Patch)
- Patchname Cursor Pos. +1 = [CRSR →] or [+] or [>]
- Patchname Cursor Pos. -1 = [CRSR ←(+SHIFT)] or [-] or [<]
- [INS DEL] or [CLR HOME] delete the patchname after patchname editing (this do not delete the patch data!).
- Format Bankstick - Please note: Patch 1 to 127 will written with the current Patch Data. For instance: the User modify the MIDI Channel Tone A to 8. Now every Bankstick Patch (1 -127) will have the MIDI Channel 8 (@Tone A) after Bankstick formatting (in this way it is easy to predefine a Patch Setup for all 127 Bankstick Patches).

From:

<http://midibox.org/dokuwiki/> - **MIDIbox**

Permanent link:

[http://midibox.org/dokuwiki/doku.php?id=midibox\\_ay\\_patch\\_menu&rev=1259674559](http://midibox.org/dokuwiki/doku.php?id=midibox_ay_patch_menu&rev=1259674559)

Last update: **2009/12/01 13:35**

