



MB SEQ functions - quick reference

Detailed info for options and functions is available at http://www.ucapps.de/midibox_seq_manual_m.html

#	Function	Description / Options									
Dedicated button functions (these can vary depending on panel design and MBSEQ_HW.V4 file)											
1	Pattern 1,2,3,4	Select pattern/track group - G1, G2, G3, G4									
2	Track 1,2,3,4	Select track within track group - T1, T2, T3, T4 (16 tracks are available in total)									
3	Trigger layer A,B,C	Select trigger layer A or B or C. Holding C opens trigger layer selection menu and allows to select others <html>	Gate	Acc	Roll	Glide	Skip	R.G(random gate)	R.V(random value)	No FX	</html>
4	Parameter layer A,B,C	Select parameter layer A and B. C switches between C & D or if <i>Pressed&Hold</i> opens parameter layer selection menu and allows to select others. Four parameter layers available by default, but CC, Pitch, Prob, Delay can be added via trigger selection menu (?)  Fix Me! <html>	Note	Vel	Length	Roll	</html>				
5	Step View	View and select steps if more than 16 are used <html>	1..16	17..32	...etc</html>						
6	Pattern	Select/load pattern/track group G1, G2, G3, G4 from SD memory location									
7	Song	Select song parameters <html>	Song #	Position	Action {Stop; x1..x16; Jump Pos; Jump Song; Mixer; Tempo; Mutes}	Select patterns G1,G2,G3,G4	</html>				

#	Function	Description / Options										
8	Edit	Enter edit mode to edit parameter layer step values and set trigger layer steps										
9	Mute	Quickly mute/unmute tracks 1...16										
10	Solo	Solo current track										
11	←/→ (Left/Right)	Move cursor position (Left has limited usage)										
12	+/- (Inc/Dec)	Same as Jog Dial encoder - increases/decreases the current value										
13	Exit	Quickly exit to top menu										
14	Select	(Press&Hold) Select steps to be controlled by All function (obviously has usage in other situations as well) 										
15	All	Edit all selected steps set with Select function										
16	Copy	Copy steps from selected # to # (Selection can be edited by Select function)										
17	Paste	Paste copied steps starting from # step (Selection can be edited by Select function)										
18	F1 (Clear)	(Press&Hold) Wipes selected track (Other functions can be assigned in MBSEQ_HW.V4 file)										
19	F2 (Select track)	(Press&Hold) Selects track (Other functions can be assigned in MBSEQ_HW.V4 file)										

#	Function	Description / Options									
20	F3 (Select parameter layer)	(Press&Hold) Selects parameter layer (Other functions can be assigned in MBSEQ_HW.V4 file)									

4	a	b
---	---	---

From: <https://midibox.org/dokuwiki/> - **MIDIbox**

Permanent link: https://midibox.org/dokuwiki/doku.php?id=midibox_seq_quick_reference&rev=1273338752

Last update: **2010/05/08 17:12**

