

SCP and MSA #defines for the SpeakJet



ImportantNote:

This file is currently under development and can change radically!

Maybe you want to wait some days until this note disappears to add your SJ-Definitions

It can be used for your C-based MBHP_IIC_SpeakJet Project:

Feel free to edit and add defines!

```
/*
 * IIC_SpeakJetDefines.h
 * kII.2
 *
 * Created by Michael Markert, audiocommander.de on 20.05.06
 * Based on Speakjet control codes from July 27, 2004 version of Speakjet
Manual
 * and ASM-Version of Doug Elliott, VA3DAE
 *
 * Released under CreativeCommons 2.5 by-nc-sa
 * http://creativecommons.org/licenses/by-nc-sa/2.5/
 */

#ifndef _IIC_SPEAKJETDEFINES_H
#define _IIC_SPEAKJETDEFINES_H

// ***** SPEAKJET SCP ***** //
// Serial Control Protocol
#ifdef _DEBUG_C
    #pragma mark -
    #pragma mark SCP
#endif

// escape character ('\') 0x5C to enter SCP Mode
#define SCP_ESCAPE                '\\\
#define SCP_SEL0                  '0'
#define SCP_SEL1                  '1'
#define SCP_SEL2                  '2'
#define SCP_SEL3                  '3'
#define SCP_SEL4                  '4'
#define SCP_SEL5                  '5'
#define SCP_SEL6                  '6'
#define SCP_SEL7                  '7'
#define SCP_EXIT                  'X'
```

```

#define SCP_READY          'V'
#define SCP_CLEAR_BUFFER  'R'
#define SCP_START         'T'
#define SCP_STOP          'S'

#define SCP_MEMTYPE       'H'
#define SCP_MEMADDR       'J'
#define SCP_MEMWRT        'N'

#define SCP_RESET         'W'

// ***** SPEAKJET SCP REGISTERS ***** //
// SCP Registers & MAX Values
#ifdef _DEBUG_C
    #pragma mark -
    #pragma mark SCP REGISTERS & MAX VALUES
#endif

// == SCP_MEMTYPE (H) ==
#define SCP_MEMTYPE_REGISTER '0'
#define SCP_MEMTYPE_EEPROM_H '3'
#define SCP_MEMTYPE_EEPROM_L '2'

// == SCP_MEMADDR (J) ==
// Envelope
#define SCP_ENV_FREQ          '0'
#define SCP_ENV_CTRL          '8'
/* Oscillator Frequency Register
#define SCP_OSC1_FREQ          '1'
#define SCP_OSC2_FREQ          '2'
#define SCP_OSC3_FREQ          '3'
#define SCP_OSC4_FREQ          '4'
#define SCP_OSC5_FREQ          '5' */
/* Oscillator Level Register
#define SCP_OSC1_LEVEL         11
#define SCP_OSC2_LEVEL         12
#define SCP_OSC3_LEVEL         13
#define SCP_OSC4_LEVEL         14
#define SCP_OSC5_LEVEL         15*/
// Distortion
#define SCP_DISTORTION         '6'
// Master
#define SCP_MASTER_VOLUME     '7'

// == SCP_MEMWRT (N) ==
// ENVType (send ENVType + ENVState!)
#define SCP_ENV_SAW            0x0
#define SCP_ENV_SINE           0x1
#define SCP_ENV_TRIANGLE       0x2

```

```
#define SCP_ENV_SQUARE          0x3
//   ENVState (send ENVType + ENVState!)
#define SCP_ENV_OSC123          0x40
#define SCP_ENV_OSC45           0x80
//   Default values
#define SCP_FREQ_DEFAULT        440
#define SCP_LEVEL_DEFAULT       20    // 63 MAX for Mixer 1: OSC 1, 2 & 3
//   Maximum accepted values
#define SCP_FREQ_MAX             3999
#define SCP_LEVEL_MAX            31
#define SCP_DISTORTION_MAX       255
#define SCP_MASTER_VOLUME_MAX   255

// ***** SPEAKJET MSA ***** //
// Mathematical Sound Architecture
#ifdef _DEBUG_C
    #pragma mark -
    #pragma mark MSA Control Codes
#endif

// 0 - 31 CONTROL CODES
#define MSA_PAUSE0              0
#define MSA_PAUSE1              1
#define MSA_PAUSE2              2
#define MSA_PAUSE3              3
#define MSA_PAUSE4              4
#define MSA_PAUSE5              5
#define MSA_PAUSE6              6

#define MSA_NEXTFAST            7
#define MSA_NEXTSLOW            8
#define MSA_NEXTHIGH            14
#define MSA_NEXTLOW             15

#define MSA_WAIT                16

#define MSA_VOLUME              20
#define MSA_SPEED               21
#define MSA_PITCH               22
#define MSA_BEND                23

#define MSA_PORTCTR             24
```

```
#define MSA_PORT          25

#define MSA_REPEAT        26

#define MSA_CALLPHRASE    28
#define MSA_GOTOPHRASE    29

#define MSA_DELAY         30
#define MSA_RESET         31

// 32 - 127 (Reserved)
#ifdef _DEBUG_C
    #pragma mark MSA (Reserved)
#endif

// 128 - 254 SOUND_CODES
#ifdef _DEBUG_C
    #pragma mark MSA Sound Codes
#endif

// MSA Sound Codes: Phonemes
#define MSAPH_IY          128
#define MSAPH_IH          129
#define MSAPH_EY          130
#define MSAPH_EH          131
#define MSAPH_AY          132
#define MSAPH_AX          133
#define MSAPH_UX          134
#define MSAPH_OH          135
#define MSAPH_AW          136
#define MSAPH_OW          137
#define MSAPH_UH          138
#define MSAPH_UW          139
#define MSAPH_MM          140
#define MSAPH_NE          141
#define MSAPH_NO          142
#define MSAPH_NGE         143
#define MSAPH_NGO         144
#define MSAPH_LE          145
#define MSAPH_LO          146
#define MSAPH_WW          147
#define MSAPH_RR          148
#define MSAPH_IYRR        149
#define MSAPH_EYRR        150
#define MSAPH_AXRR        151
#define MSAPH_AWRR        152
#define MSAPH_OWRR        153
#define MSAPH_EYIY        154
#define MSAPH_OHIY        155
#define MSAPH_OWIY        156
#define MSAPH_OHIH        157
```

```
#define MSAPH_IYEH          158
#define MSAPH_EHLL          159
#define MSAPH_IYUW          160
#define MSAPH_AXUW          161
#define MSAPH_IHWW          162
#define MSAPH_AYWW          163
#define MSAPH_OWWW          164
#define MSAPH_JH            165
#define MSAPH_VV            166
#define MSAPH_ZZ            167
#define MSAPH_ZH            168
#define MSAPH_DH            169
#define MSAPH_BE            170
#define MSAPH_B0            171
#define MSAPH_EB            172
#define MSAPH_0B            173
#define MSAPH_DE            174
#define MSAPH_DO            175
#define MSAPH_ED            176
#define MSAPH_OD            177
#define MSAPH_GE            178
#define MSAPH_GO            179
#define MSAPH_EG            180
#define MSAPH_0G            181
#define MSAPH_CH            182
#define MSAPH_HE            183
#define MSAPH_HO            184
#define MSAPH_WH            185
#define MSAPH_FF            186
#define MSAPH_SE            187
#define MSAPH_SO            188
#define MSAPH_SH            189
#define MSAPH_TH            190
#define MSAPH_TT            191
#define MSAPH_TU            192
#define MSAPH_TS            193
#define MSAPH_KE            194
#define MSAPH_KO            195
#define MSAPH_EK            196
#define MSAPH_OK            197
#define MSAPH_PE            198
#define MSAPH_PO            199

// MSA Sound Codes: Robot
#define MSAFX_ROBOT_0      200
#define MSAFX_ROBOT_1      201
#define MSAFX_ROBOT_2      202
#define MSAFX_ROBOT_3      203
#define MSAFX_ROBOT_4      204
#define MSAFX_ROBOT_5      205
#define MSAFX_ROBOT_6      206
```

```
#define MSAFX_ROBOT_7      207
#define MSAFX_ROBOT_8      208
#define MSAFX_ROBOT_9      209

// MSA Sound Codes: Alarms
#define MSAFX_ALARM_0      210
#define MSAFX_ALARM_1      211
#define MSAFX_ALARM_2      212
#define MSAFX_ALARM_3      213
#define MSAFX_ALARM_4      214
#define MSAFX_ALARM_5      215
#define MSAFX_ALARM_6      216
#define MSAFX_ALARM_7      217
#define MSAFX_ALARM_8      218
#define MSAFX_ALARM_9      219

// MSA Sound Codes: Beeps
#define MSAFX_BEEP_0       220
#define MSAFX_BEEP_1       221
#define MSAFX_BEEP_2       222
#define MSAFX_BEEP_3       223
#define MSAFX_BEEP_4       224
#define MSAFX_BEEP_5       225
#define MSAFX_BEEP_6       226
#define MSAFX_BEEP_7       227
#define MSAFX_BEEP_8       228
#define MSAFX_BEEP_9       229

// MSA Sound Codes: Biological
#define MSAFX_BIO_0         230
#define MSAFX_BIO_1         231
#define MSAFX_BIO_2         232
#define MSAFX_BIO_3         233
#define MSAFX_BIO_4         234
#define MSAFX_BIO_5         235
#define MSAFX_BIO_6         236
#define MSAFX_BIO_7         237
#define MSAFX_BIO_8         238
#define MSAFX_BIO_9         239

// MSA Sound Codes: DTMF
#define MSAFX_DTMF_0        240
#define MSAFX_DTMF_1        241
#define MSAFX_DTMF_2        242
#define MSAFX_DTMF_3        243
#define MSAFX_DTMF_4        244
#define MSAFX_DTMF_5        245
#define MSAFX_DTMF_6        246
#define MSAFX_DTMF_7        247
#define MSAFX_DTMF_8        248
#define MSAFX_DTMF_9        249
```

```
#define MSAFX_DTMF_S      250
#define MSAFX_DTMF_R      251

// MSA Sound Codes: Misc
#define MSAFX_SONAR_PING  252
#define MSAFX_PISTOLSHOT  253
#define MSAFX_WOW         254

// 255: End of Phrase
#ifdef _DEBUG_C
    #pragma mark MSA EOP
#endif

#define MSA_EOP           255

#endif /* _IIC_SPEAKJETDEFINES_H */
```

From:

<https://midibox.org/dokuwiki/> - **MIDIbox**

Permanent link:

https://midibox.org/dokuwiki/doku.php?id=speakjet_definition_list&rev=1160904901

Last update: **2006/12/05 14:28**

